



# 100 Watt Commercial Audio Power Amplifier

Model No: WL-AMP-100W-70V-ROEM


## Description

The Wahsega Roemtech 100 Watt Commercial Audio Power Amplifier (70V) can power multiple Commercial Speakers from Wahsega.

With 100 watts of power, this Commercial Audio Power Amplifier features HummBuster® Technology. This allows the end user or installer to “switch off” annoying hums or buzzes without affecting audio quality. Featuring advanced technology, this amplifier provides the power needed for large building such as warehouses, gyms, and cafeterias by daisy chaining multiple speakers.

## Key Features

- 100 Watts
- HummBuster® Technology
- Daisy-chain multiple analog speakers
- Auto Clip Limiter
- Two Channel Mixer
- Plenum Rated
- Fit up to 3 on 1 RU shelf

Job Name:	Date:	Location:
Notes:		

# 100 Watt Commercial Audio Power Amplifier

Model No: WL-AMP-100W-70V-ROEM

Specification Submittal

## Specifications

- Power: 100 watts RMS
- Frequency response: 60Hz – 20kHz +3db @1kHz
- Input 1: Stereo RCA - mixable
- Input 2: Stereo 3.5mm - mixable
- Speaker Out: 70V Mono
- Power Supply: 24V @4.5 Amps - 108 Watts
- Temperature Range: -40°C to +80°C
- Weight: 0.95 lbs (amp only)
- Dimensions: 1.4" H x 5.85" W x 5.9" D
- Sleep Mode: 20 minutes, defeatable
- Surge Protection: 10,000 Volts
- Warranty: 3 years limited


## Compatible Devices

Requires a Wahsega Zone Controller

- Carina Model Number: WL-ZN-CTR-1CH-CAR
- InformaCast Model Number: WL-ZN-CTR-1CH-INF

Compatible Speakers

- 70V 2x2 Commercial Ceiling Speaker: WL-SPKR-22-20W-CAR
- 70V Commercial Outdoor Speaker: WL-SPKR-OF-20W-CAR

Job Name:	Date:	Location:
Notes:		

# 100 Watt Commercial Audio Power Amplifier

Model No: WL-AMP-100W-70V-ROEM

Specification Submittal

## Dimensions

Front View



Rear View



Job Name:	Date:	Location:
Notes:		